### NNH4-45A-R6



# 12-port sector antenna, 4x 698–896 and 8x 1695–2360 MHz, 45° HPBW, 6x RET

- Array configuration provides capability for 4T4R (4x MIMO) on Low band and Dual 4T4R (4x MIMO) on High band
- Optimized SPR performance across all operating bands
- Excellent wind loading characteristics
- Features broadband Low Band (698-896 MHz) and High Band (1695-2360 MHz) arrays for 4T4R (4X MIMO) capability for Band 14, AWS, PCS and WCS applications
- Independent tilt for all arrays

#### Alternative products available:

NNH4-45A-R3B-V1 12-port sector antenna, 4x 698-896 and 8x 1695-2360 MHz, 45° HPBW, 3x RET

### General Specifications

Antenna Type Sector

Band Multiband

Color Light Gray (RAL 7035)

**Grounding Type**RF connector inner conductor and body grounded to reflector and mounting

bracket

Performance Note Outdoor usage

Radome MaterialFiberglass, UV resistantRadiator MaterialLow loss circuit board

Reflector Material Aluminum

RF Connector Interface 4.3-10 Female

**RF Connector Location** Bottom

RF Connector Quantity, high band 8
RF Connector Quantity, mid band 0
RF Connector Quantity, low band 4
RF Connector Quantity, total 12

### Remote Electrical Tilt (RET) Information

**RET Hardware** CommRET v2

**RET Interface** 8-pin DIN Female | 8-pin DIN Male

ANDREW® an Amphenol company

# NNH4-45A-R6

**RET Interface, quantity** 1 female | 1 male

Input Voltage 10-30 Vdc

Internal RET High band (4) | Low band (2)

Power Consumption, active state, maximum 8 W Power Consumption, idle state, maximum 1 W

Protocol 3GPP/AISG 2.0

**Dimensions** 


 Width
 457 mm | 17.992 in

 Depth
 178 mm | 7.008 in

 Length
 1399 mm | 55.079 in

 Net Weight, antenna only
 27.2 kg | 59.966 lb


### Array Layout



Array ID	Frequency (MHz)	RF Connector	RET (MRET)	AISG RET UID
R1	698-896	1 - 2	1	CPxxxxxxxxxxxMM.1
R2	698-896	3 - 4	2	CPxxxxxxxxxxxMM.2
Y1	1695-2360	5 - 6	3	CPxxxxxxxxxxxMM.3
Y2	1695-2360	7 - 8	4	CPxxxxxxxxxxxMM.4
Y3	1695-2360	9 - 10	5	CPxxxxxxxxxxxMM.5
Y4	1695-2360	11 - 12	6	CPxxxxxxxxxxxMM.6

(Sizes of colored boxes are not true depictions of array sizes)

### Port Configuration



### **Electrical Specifications**

**Impedance** 50 ohm

**Operating Frequency Band** 1695 – 2360 MHz | 698 – 896 MHz

Polarization ±45°

**Total Input Power, maximum** 900 W @ 50 °C

### **Electrical Specifications**

	R1,R2	R1,R2	Y1-Y4	Y1-Y4	Y1-Y4	Y1-Y4
Frequency Band, MHz	698-806	806-896	1695-1880	1850-1990	1920-2180	2300-2360
RF Port	1-4	1-4	5-12	5-12	5-12	5-12
Gain, dBi	12.6	13.5	15.1	15.8	16.6	16.9
Beamwidth, Horizontal, degrees	49	44	45	42	40	36
Beamwidth, Vertical, degrees	36	30.4	15.2	13.7	12.9	11.5
Beam Tilt, degrees	2-18	2-18	2-12	2-12	2-12	2-12
USLS (First Lobe), dB	17	17	15	17	17	18
Front-to-Back Ratio at 180°, dB	31	35	32	33	34	33
Isolation, Cross Polarization,	25	25	25	25	25	25

Page 3 of 4



## NNH4-45A-R6

dB						
Isolation, Inter-band, dB	25	25	25	25	25	25
VSWR   Return loss, dB	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0
PIM, 3rd Order, 2 x 20 W, dBc	-150	-150	-150	-150	-150	-150
Input Power per Port at 50°C, maximum, watts	300	300	250	250	250	200

### Mechanical Specifications

 Wind Loading @ Velocity, frontal
 788.0 N @ 150 km/h (177.1 lbf @ 150 km/h)

 Wind Loading @ Velocity, lateral
 157.0 N @ 150 km/h (35.3 lbf @ 150 km/h)

 Wind Loading @ Velocity, maximum
 788.0 N @ 150 km/h (177.1 lbf @ 150 km/h)

 Wind Loading @ Velocity, rear
 692.0 N @ 150 km/h (155.6 lbf @ 150 km/h)

 Wind Speed, maximum
 241.4 km/h (150 mph)

### Packaging and Weights

 Width, packed
 526 mm | 20.709 in

 Depth, packed
 283 mm | 11.142 in

 Length, packed
 1566 mm | 61.654 in

 Weight, gross
 36.9 kg | 81.35 lb

#### Regulatory Compliance/Certifications

#### Agency Classification

ISO 9001:2015 Designed, manufactured and/or distributed under this quality management system

#### Included Products

BSAMNT-2F – Mounting bracket for cylindrical pipe installations (60-115mm pipe diameter) for fix mechanical tilt applications.

#### \* Footnotes

**Performance Note** Severe environmental conditions may degrade optimum performance

